

Product Overview

COMFORT DIGISYSTEM

Microphones



Conference
Microphone DC10



Microphone
DM05



Microphone
DM10

Features

Type of microphone	Long range	Close range	Close range
Integrated receiver			
Eavesdrop-secure	◆	◆	◆
Zoom-microphone	◆		
Microphone modes	4	1	1
Transient control	◆		
Noise reduction	◆		
Display and language choice	◆		◆
Function indicator	◆	◆	◆
Mobile phone	◆		
Socket for headphones	◆		
Line-in	◆		◆
Induction loop			
Volume control	◆		◆
PIN-Code	◆		◆
Bluetooth	◆		
Automatic Gain Control (AGC)	◆	◆	◆
Perceptual Speech Enhancement (PSE)	◆		
SecureStream Technology (SST)	◆	◆	◆
Free Frequency Check (FFC)	◆		◆
Free Channel Request (FCR)			◆
Frequency range transmitter	904 - 927 MHz	904 - 927 MHz	904 - 927 MHz
Frequency range receiver			
Operating time	10 h	6 h	10 h
Charging time	5 h	2 h	2 h
Size	4.53 x 2.44 x 0.55 inch	2.2 x 1.02 x 0.35 inch.	3.31 x 1.53 x 0.55 inch.
Weight	3.17 oz.	0.56 oz.	1.59 oz.
Range	100 feet	100 feet	100 feet
Battery	Li-Polymer	Li-Polymer	Li-Polymer

USA and Canada only

Recommended for:

Mobile phone	◆		
Dialogue between 2 persons		◆	◆
Meetings and group work	◆		
In the car		◆	◆
Watching TV	◆		◆
Integrated pupil (1 teacher)		◆	◆
Integrated pupil (2 teachers)		◆	◆
Special school	◆		◆
Lecture		◆	◆
Students with concentration problems			◆



Microphone
DM30



Microphone
DM90

Receivers



Receiver
DH10



Receiver
DT20

Features

Type of microphone	Close range	Close range		
Integrated receiver	◆	◆		
Eavesdrop-secure	◆	◆	◆	◆
Zoom-microphone		◆		
Microphone modes	1	2		
Transient control				
Noise reduction				
Display and language choice	◆	◆	◆	
Function indicator	◆	◆	◆	
Mobile phone		◆		
Socket for headphones	◆	◆	◆	
Line-in	◆	◆		
Induction loop	◆	◆	◆	
Volume control	◆	◆	◆	
PIN-code	◆	◆	◆	
Bluetooth		◆		
Automatic Gain Control (AGC)	◆	◆		
Perceptual Speech Enhancement (PSE)				
SecureStream Technology (SST)	◆	◆	◆	◆
Free Frequency Check (FFC)	◆	◆	◆	
Free Channel Request (FCR)	◆			
Frequency range transmitter	904 - 927 MHz	904 - 927 MHz		
	w 2.40 - 2.48 GHz			
Frequency range receiver	904 - 927 MHz		904 - 927 MHz	904 - 927 MHz
	w 2.40 - 2.48 GHz			
Operating time	10 h	9 h	10 h	
Charging time	3 h	3 h	2 h	
Size	3.82 x 1.61 x 0.67 inch.	3.82 x 1.61 x 0.67 inch	2.91 x 1.54 x 0.51 inch	0.33 x 0.36 x 0.5 inch.
Weight	1.91 oz.	1.94 oz.	1.23 oz.	0.035 oz.
Range	100 feet	100 feet	100 feet	100 feet
Battery	Li-Polymer	Li-Polymer	Li-Polymer	

Recommended for:

Mobile phone		◆	
Dialogue between 2 persons		◆	
Meetings and group work			
In the car		◆	
Watching TV	◆	◆	
Integrated pupil (1 teacher)			
Integrated pupil (2 teachers)	◆		
Special school	◆		
Lecture			
Students with concentration problems			

Is used with hearing instruments, cochlear-implants, bone-anchored implants, head- or ear-phones; with induction loop.

Mini-receiver that can be used with hearing instruments, cochlear-implants and bone-anchored implants.

